


Pushpam

Expanding IT Horizon



PUSHPAM

Estd. 1990

APORT 400 IP to Serial Port Converter



- 32 bit 100 MHz RISC CPU higher performance than 16bit CPU.
- Auto-detecting 10/ 100 Mbps Ethernet interface.
- Support Windows NT/ 2000 / XP/ Vista virtual COM driver.
- Support Windows 7 virtual COM driver.
- Support UNI X & Linux real TTY driver.
- Support TCP server/Client mode.
- Support UDP send/ receive mode.
- Support WEB ,TELNET and terminal setup.

APORT400 IP to Serial Port Converter Specification :	
<p>Hardware Specification:</p> <ul style="list-style-type: none"> * CPU: 32bit 100MHz MIPS CPU. * Flash ROM: 16M Byte. * SDRAM: 16M Byte. <p>LAN connection:</p> <ul style="list-style-type: none"> *Interface: 10/100Mbps 100BaseT *Connector: RJ45 <p>Serial port:</p> <ul style="list-style-type: none"> *Interface: RS232 *connector: DB9 male. *Port Number: 4 *speed: upto 230400bps. <p>NOTE: console port share with serial port 1.</p>	<p>Software Compatibility:</p> <ul style="list-style-type: none"> *TCP/IP or UDP/IP connection. *WIN NT/2000/XP/Vista Virtual COM driver. *Windows 7 Virtual COM driver. *SCO UNIX real TTY driver. <p>Power Requirement:</p> <ul style="list-style-type: none"> *5VDC @ 1200mA. <p>Environment:</p> <ul style="list-style-type: none"> *Operating temperature: 5--40C. *Operating humidity: 10--90%RH. *Storage temperature: 0--65C. *Storage humidity: 5--90%RH. <p>Dimension:</p> <ul style="list-style-type: none"> 205*135*29mm.

<p>Other relative product information:</p> <ul style="list-style-type: none"> *APORT200: IP to two RS232 serial port converter. *APORT020: IP to two ground isolated RS232 serial port converter. *APORT101: IP to one RS232 and one ground isolated RS422/485 serial port converter. *APORT040: IP to four ground isolated RS232 serial port converter. *APORT202: IP to two RS232 and two ground isolated RS422/485 serial port converter. *APORT022: IP to two ground isolated RS232 and two ground isolated RS422/485 serial port converter. *APORT800: Ethernet to 8 RS232 port. *APORT602: IP to six RS232 and two ground isolated RS422/485 serial port converter. *APORT620: IP to six RS232 and two ground isolated RS232 serial port converter. <p>***All names are the trademarks of their respective organization.</p>
--

Note : All the technical and commercial specifications of the product displayed within the brochure, box, media, color, price, etc. are subject to change without any prior notice. No claims would be entertained by Pushpam and/or it's principal vendors in this regards. For all technical and commercial matter, jurisdiction would be Pune city only.

Pushpam Group of Companies

Pushpam Computers & Softwares

Pushpam Infotech Corp.

Pushsoft Technologies

635/1-B, New Gajra Society, Bibwewadi, Pune - 411037
 Tel. No. 91+20+3091 506 /931/ 934
 Fax: 91+20+24216455
 Email: dealersales@pushpam.com, sales@pushpam.com,
 rahul_jangam@pushpam.com

Pushpam a 15 year old group is working in the various fields of Information Technology . Software development, Gas distribution, Computer hardware imports/ distribution , manufacturing of ayurvedic medicines, food processing and export etc. Working in cutting edge technology products, Pushpam always aggressive and efficient towards all the projects. In IT sector Pushpam is active since last 14 years and is currently working on technologies like Information Kiosk / Transaction Kiosk /Touch screens, POS products like Thermal printers, barcode scanners, Customer display, complete POS systems and Multi port serial card solutions. Pushpam is already in to imports of all these products from Taiwan and other parts of the world and offers the complete solution and best support for all these products. Pushpam has always believed in the best product and best support at the best price.

